

泰克电流测试解决方案

	带宽 Hz	峰值脉冲 A	最大交流 峰峰值	最大直流 A	安培秒积 A*S	钳口直径 mm	MSO/DPO4000	MSO/DPO3000	MSO/DPO2000	TDS3000C	TPS2000	TDS2000/1 000B	其他厂家 示波器
电流测试系统													
TCPA300 TCP312	DC-100M	50A	60A	5A @ 1A/V 30A @10A/V	50A*uS 500A*uS	3.8	●	●	●	●	●	●	●
TCPA300 TCP305	DC-50M	50A	100A	25A @ 5A/V 50A @ 10A/V	500A*uS --	3.8	●	●	●	●	●	●	●
TCPA300 TCP303	DC-15M	150A	424A	25A @ 5A/V 150A @ 50A/V	3000A*uS 15000A*uS	21X25	●	●	●	●	●	●	●
TCPA400 TCP404XL	DC-2M	750A	1414A	750A	--	21X25	●	●	●	●	●	●	●
直接连接型电流探头													
TCP0030	DC-120M	50A	84A	5A 30A	50A*uS 500A*uS	3.8	●	●	●+P				
TCP0150	DC-20M	150A	424A	25A @25A/V 150A @ 150A/V	3000A*uS 15000A*uS	21x25	●	●	●+P				
TCP202	DC-50M	50A	40A	15A	500A*uS	3.8	● + Δ	● + Δ		●			●+1103
其他电流探头													
P6021	120-60M	250A	15A	0.5A	500A*uS	3.8	●	●	●	●	●	●	●
P6022	935-120	100A	6A	0.2A	9A*uS	3.58	●	●	●	●	●	●	●
CT1	25K-1G	12A	1.4A	0.3A	1A*uS	1.78	●	●	● Ω	●			
CT2	1.2K-200	36A	7A	0.3A	50A*uS	1.32	●	●	● Ω	●	● Ω	● Ω	● Ω
CT6	250K-2G	6A	0.7A	0.2A	0.25A*uS	0.8	●						
A621	5-50K	2000A	4000A	--	1A*uS	54	●	●	●	●	●	●	●
A622	DC-100K	100A	200A	100A	--	11.8	●	●	●	●	●	●	●

- 可以直接连接使用
- + Δ 连接TPA-BNC适配器使用
- + P 可以直接连接使用，主机需要加配TEKVPI电源适配器

- Ω 通过50欧姆终端适配器连接
 - +1103 连接1103电源使用
- 详细信息请查阅：www.tek.com/probe/